

COMPREHENSIVE SERVICES

We offer competitive repair and calibration services, as well as easily accessible documentation and free downloadable resources.

SELL YOUR SURPLUS

We buy new, used, decommissioned, and surplus parts from every NI series. We work out the best solution to suit your individual needs.

 Sell For Cash  Get Credit  Receive a Trade-In Deal

OBSOLETE NI HARDWARE IN STOCK & READY TO SHIP

We stock **New**, **New Surplus**, **Refurbished**, and **Reconditioned** NI Hardware.



Bridging the gap between the manufacturer and your legacy test system.

 1-800-915-6216

 www.apexwaves.com

 sales@apexwaves.com

All trademarks, brands, and brand names are the property of their respective owners.

Request a Quote

 **CLICK HERE**

SCXI-1338

SCXI™-1338 TERMINAL BLOCK

Introduction

This document contains information and step-by-step instructions for verifying the precision resistors on the National Instruments SCXI-1338 terminal block.

What Is Calibration?

Calibration consists of verifying the measurement accuracy of a device and adjusting for any measurement error. *Verification* is measuring performance of a device and comparing the results to the factory specifications. Because the SCXI-1338 is not user-adjustable, calibrating this device consists of verifying the performance only.

Why Should You Verify?

The accuracy of electronic components drifts with time and temperature, which can affect measurement accuracy as the device ages. Verification ensures that your device still meets National Instruments (NI) standards. If the results of the verification procedure indicate that your SCXI-1338 is out of specification, return it to NI for repair or replacement.

How Often Should You Verify?

The measurement accuracy requirements of your application determine how often you should verify the SCXI-1338 module. NI recommends that you perform a complete calibration at least once every year. You can shorten this interval to 90 days or six months based on the demands of your application.

Equipment and Other Test Requirements

This section describes the equipment, software, documentation, and test conditions needed to verify the performance of the SCXI-1328.

Test Equipment

Verification requires a multiranging 5 1/2 digit digital multimeter (DMM) with 15 ppm accuracy.

NI recommends that you use the NI 4060 or HP 34401 DMM to verify the performance of an SCXI-1338.

If one of these instruments is not available, use the accuracy requirements listed above to select a substitute calibration standard.

Software and Documentation

No software is required to verify the performance of the SCXI-1338. All required documentation is found in this calibration procedure. If you would like more information on the product, refer to the *SCXI-1338 Current Input, High-Voltage Terminal Block Installation Guide*.

Test Conditions

Follow these guidelines to optimize the connections and the environment during verification:

- Keep connections to the SCXI terminal block short. Long cables and wires act as antennae, picking up extra noise that can affect measurements.
- Use shielded copper wire for all cable connections to the device. Use twisted-pair wire to eliminate noise and thermal offsets.
- Keep relative humidity below 80%.
- Maintain temperature between 15 and 35 °C.
- Use 4-wire resistive measurements when possible as they are generally more accurate than 2-wire measurements.

Verification Procedures

Use the following procedure to verify the performance of the precision resistors on the SCXI-1338. These resistors convert current to voltage.

Verifying the Performance of Precision Resistors

1. Open the terminal block enclosure by removing the top cover.
2. Locate R0 on the printed circuit board. This precision resistor is associated with channel 0 on the terminal block.
3. Using a calibrated DMM, measure the resistance (R_{meas}) between the two exposed leads of the resistor.
4. Using a calibrated instrument, measure the ambient temperature (T_{amb} in °C) of the terminal block.
5. Calculate the following:

$$R_{adj} = R_{meas} - (T_{amb} - 25) \times 0.00001$$

6. Determine if resistor performance is meeting the specification.
 - If $248.751 \Omega \leq R_{adj} \leq 249.249 \Omega$, you have verified the performance of the resistor.
 - If $R_{adj} > 249.249 \Omega$, the terminal block is non-functional—repair or replace it.
 - If $R_{adj} < 248.751 \Omega$, the terminal block is non-functional—repair or replace it.
7. Repeat steps 2 through 8 using the remaining resistor locations:
 - R1 (channel 1)
 - R2 (channel 2)
 - R3 (channel 3)
 - R4 (channel 4)
 - R5 (channel 5)
 - R6 (channel 6)
 - R7 (channel 7)

You have completed verifying the performance of the SCXI-1338.